Switch disconnector for solar application according to IEC 60947-3 by KEMA








Layer No.	Front Side		Symbol	Rear Side		On Positions			
	Left	Right	Symbol	Left	Right	1	2	3	4
			-/-						
			-/-						
			-/-						
			-/-						
			-/-						
			-/-						
			-/-						
			-/-						
5	+2		-/-	+2		X			
4		-2	-/-		-2	X			
3	-1		-/-	-1		X			
2		+1	-/-		+1	X			
1			empty						

Contacts are made in "X" marked position.
Symbols for interconnection: [

	Symbols for interconnection: [
Technical data	Symbol	Mirit		Unit			
nominal voltage (DC poles)	Ue		1000	V dc			
nominal current (DC poles)	le		16	A dc			
nominal voltage (second rating DC poles, if requested)	Ue		850	V dc			
nominal current (second rating DC poles, if requested)	le		20	A dc			
nominal voltage (third rating DC poles, if requested)	Ue		800	V dc			
nominal current (third rating DC poles, if requested)	le		25	A dc			
method of mounting	DIN rail and	or Base mounting [B]					
number of DC poles			4				
utilization category DC	DC-21B						
actuator	standard bl	ack [A]					
positions	OFF at 12 h	r, ON at 3 hr [E]					
rated impulse withstand voltage	Uimp		8	kV			
insulation voltage	Ui		1000	V			
rated thermal current uninterrupted duty	lu		16	Α			
rated short-time withstand current (1s)	Icw		750	Α			
rated short-circuit making capacity	Icm		1,4	kA			
rated conditional short-circuit current			5	kA			
max power dissipation			1,4	W			
method of operation	independer	t manual operation					
minimum required dimensions of enclosures L x W x H*		124	1 x 47 x 84,5	mm			
* see the drawing for the height of the switch. The number of layers N is:			5				
Shaft length				mm			
Enclosure depth from inside bottom to outside top, required for the switch and	d knob		51,5	mm			
tightening torque terminal screws M4 , min max.		1,5	1,7	Nm			
tightening torque M3 screw in the standard black knob, min max.		0,5	0,7	Nm			
tightening torque for the nut on the single hole mounting knob, min max.		1,8	2,0	Nm			
minimum required fine wire cross-section: IEC60947-1, table 9			2,5	mm2			
ambient temperature allowed between		- 2	0 to + 70 °C	.c			
storage temperature allowed between		- 4	0 to + 80 °C	*C			
maximum relative humidity, without condensation at 20°C			90	%			
pollution degree			2				
IP rating terminals			IP20				
IP rating gland of the shaft in case of single hole panel mounting							
nominal voltage (AC poles)	Ue			V ac			
nominal current (AC poles)	le			Aac			
number of AC poles							
auxiliary contact(s)			No auxilia	ry contac			
auxiliary contact ratings							
weight			254	g			
accessories:	181						
Superior Switch Solutions							








Mounting instructions

In the application all ratings have to be respected. When building the switch in an enclosure, the space envelope must be respected according to the applicable standards. The terminals, without interconnection can take copper wires up to 6 mm2. The recommended Spade Tongue Terminals may have a maximum width of 9 mm. For CSA and UL applications, registered Spade Tongue Terminals must be used. The registration numbers are UL: E13288 and CSA: LR7189 (for instance type 165015 from Tyco). After mounting, the wiring must be checked and the switch must operate smoothly.

Maintenance

The X type switches are designed for a very long life but it is advised to do some simple yearly maintenance.

- Check the installation for signs of overload or overheating. The terminals may not exceed the limit of 85°C under full load.
- By operating the switch a few times (5x) the contacts will clean themselves and the switch will have a longer life.



Dimensions, specifications and data shown could be subject to change without notice.

Superior Switch Solution