

LKD 34S. Specification

Model Number	Maximum Allowable Voltage		Varistor Voltage		Clamping voltage (max.)		Rated voltage reference	8/20us Peak Current		Maximum Energy (Joule) 10/1000 @ 1KHz	Typical Capacitance (Reference)		
	AC.Rms (V)	DC (V)	V1.0mA(V)		VC (V)	IP (A)		In. 10times (KA)	I Max. (KA)				
Normal			min.	max.						μs	(pf)		
34S470KA	30	38	42	52	93	60	DC 24	10	20	96	35000		
34S560KA	35	45	50	63	110	60				115	29500		
34S680KA	40	56	61	75	135	60				136	24200		
34S820KA	50	65	74	90	135	300	DC 48			156	17950		
34S101KA	60	85	90	110	165	300				195	15000		
34S121KA	75	100	108	132	200	300	DC 60			235	12200		
34S151KA	95	125	135	165	250	300				296	10000		
34S181KA	115	150	162	198	300	300	AC 100	20	50	350	8250		
34S201KA	130	170	185	225	340	300	AC 125			400	6750		
34S221KA	140	180	198	242	360	300				450	6400		
34S241KA	150	200	222	270	395	300				480	5650		
34S271KA	180	225	256	310	455	300				540	5100		
34S301KA	190	250	270	330	500	300	AC 250			600	4510		
34S331KA	210	275	297	363	550	300				656	4150		
34S361KA	230	300	324	396	595	300	Telephone test			745	3750		
34S391KA	250	320	362	440	650	300	AC 250			20	50	830	3500
34S431KA	275	350	387	473	710	300						920	2950
34S471KA	300	385	423	517	775	300		1000	2880				
34S511KA	320	415	459	561	845	300		1060	2650				
34S561KA	350	460	504	616	925	300		1150	2450				
34S621KA	385	505	558	682	1025	300		1250	2200				
34S681KA	420	560	612	748	1120	300		1250	2000				
34S711KA	440	585	644	786	1180	300		1280	1950				
34S751KA	460	615	675	825	1240	300		20	45			1280	1820
34S781KA	485	640	702	858	1290	300						1350	1750
34S821KA	510	670	738	902	1355	300	1395			1650			
34S911KA	550	745	819	1001	1500	300	1475			1500			
34S951KA	575	760	855	1045	1570	300	1485			1430			
34S102KA	625	825	900	1100	1650	300	1550			1350			
34S112KA	680	895	990	1210	1815	300	1700			1230			
34S122KA	750	980	1150	1320	1980	300	1750			1135			
34S142KA	850	1120	1315	1540	2310	300	AC 380 or G			15	40	1750	970
34S162KA	1000	1320	1550	1760	2640	300						2000	840
34S182KA	1100	1485	1700	1980	2970	300		2000	800				